



# PHASE INDICATOR KEW 8031/8031F



# Long selling models were renewed with the design and the measurement category!

### • Two Functions in One Unit

Presence of open phase can be checked by the lamps, and the phase sequence can be indicated by the rotating disk.

### High Reliability

Wide measuring range for 3-phase installations from 110V to 600V. Sealed against dust ensures the trouble-free performance.

Battery-free tester

KYORITSU ELECTRICAL INSTRUMENTS WORKS, LTD.

www.kew-ltd.co.jp

# Simple operation Two functions in one unit Phase check with three lamps. ΟK open phase Connect the clips to the terminals. Press the push Sequence check with rotating disk. switch button. Positive phase Reversed phase (clockwise) (counter-clockwise) PRESS TO L3 W KEW 8031/8031F Specifications Accessories KEW 8031 KEW 8031 KEW 8031F (Standard Type) (CE Type) (Fuse incorporated) Appearance

Operational voltage	110 - 600V AC (50/60Hz)		
Time limit for continuous	>500V: within 5 minutes		
Fuse			0.5A/600V (F)
Applicable standards	- *non compliant with CE	IEC 61010-1 CAT IV 300V, CAT Ⅲ 600V Pollution degree 2	
Dimensions	$106(L) \times 75(W) \times 40(D)mm$		
Weight	350g approx.		
Cord	1.5m (R: red S: white T: blue)		
Accessories	9029 (Carrying Case) Instruction manual		8923 (Fuse[0.5A/250V])* 9094 (Carrying Case) Instruction Manual
			*includec





8923 (Fuse) \*8031F



Please read the "Safety Warnings" in the instruction manual supplied with the instrument thoroughly and completely **Safety Warnings**: Failure to follow the safety rules can cause fire, trouble, electrical shock, etc. Therefore, make sure to operate the instrument on a correct power supply and voltage rating marked on each instrument.

For inquires or orders :

## **KYORITSU ELECTRICAL INSTRUMENTS** WORKS, LTD.

2-5-20, Nakane, Meguro-ku, Tokyo, 152-0031 Japan Phone:+81-3-3723-0131 Fax:+81-3-3723-0152 E-mail:info-eng@kew-ltd.co.jp

www.kew-ltd.co.jp

